

KANLUX IQ-LED ES-111 12W

Dimmer	1 IQ-LED ES-111 lamp		2 IQ-LED ES-111 lamps		4 IQ-LED ES-111 lamps	
	minimum level [%]	maximum level [%]	minimum level [%]	maximum level [%]	minimum level [%]	maximum level [%]
ELKO RS16/400 GLI	1%	94%	2%	94%	1%	94%
Varilight V-PRO (Screwfix) JQP401W 94816 (5021575581065)	8%	93%	8%	94%	8%	94%
Gira 2262 00	3%	94%	2%	93%	0%	94%
ABB 6523UJGL-214	5%	91%	5%	89%	5%	89%
ABB 2251 UCGL-92-507	0%	95%	0%	96%	0%	95%
KOPP arktis-weiß 809702013	2%	92%	2%	92%	2%	93%
GIRA Dimmer Druck-Wechsel	5%	93%	4%	93%	4%	93%
HPM Cat 400T Trailing Edge	7%	87%	7%	87%	8%	87%
LIVINGLIGHT L-N-NT441N 110/127V 50/60HZ 220V/230V 400W	1%	82%	1%	83%	1%	87%
SCHNEIDER CLIPSAL E8431EPD4	6%	94%	6%	93%	6%	93%
CLIPSAL 32E450TM	9%	94%	9%	94%	9%	94%
CLIPSAL 31E2RUDM Universal Dimmer	4%	88%	4%	89%	4%	89%
HPM Cat 250T Trailing Edge	8%	90%	8%	90%	8%	90%
CLIPSAL 32E450LM	4%	99%	4%	97%	0%	98%
CLIPSAL 32ELEDM	4%	93%	4%	93%	4%	93%

* Kanlux SA is not liable for the results of design changes introduced by the manufacturers of the above-mentioned dimmers that can affect the compatibility with Kanlux iQ-LEDDIM light sources.